



## PM5005 INTEGRATED AMPLIFIER



40 w x 2ch

CURRENT  
FEEDBACK

SYSTEM  
REMOTE

METAL  
FRONT

HDMI  
BUS

A-B

MM  
Phono

PURE  
DIRECT

green standby  
eco friendly

New to the Marantz collection, this excellent entry-level integrated amplifier breaks all the rules. That's because with current feedback architecture - the PM5005 includes this feature normally reserved for the more expensive models. This technology provides very fast and accurate signal handling, which results in perfectly balanced stereo sound reproduction as well as a very open and precise sound stage. It's also been recently enhanced with performance-optimizing discrete audio circuitry and fine-tuning components. In addition, this year's model looks a little more stylish than last year's, thanks to new elegant knob design. On top of that, it comes with a new remote and a new low-power stand-by and auto stand-by mode. But back to being an amp: the PM5005 offers 40W per channel into 8 ohm or 55W into 4 ohm, and includes a metal chassis and a front metal panel to ensure a very rigid and solid base. It also has a Phono MM equalizer, as well as a Source Direct functionality to ensure shortest signal paths. Without doubt, the PM5005 has raised the performance bar in the so-called entry level area. Great sound. Amazing versatility.

### Main Features

- Integrated Current Feedback Amplifier with 2x 40W / 8 ohm rms
- Gold Plated Inputs/Outputs incl. Phono (MM) input
- Marantz proprietary HDAM-SA3 circuits
- Selected high quality audio components
- Fully discrete volume amplifier circuit
- Tone control and Source Direct function
- High quality Speaker Terminals (A / B switchable)
- Headphone output
- System remote to control Amplifier, CD-Player and Network Player

### UPC

NA PM5005/U1B 6-99927-13085-5 Black

us.marantz.com

---

# because music matters

## PM5005

### INTEGRATED AMPLIFIER



FEATURES	PM5005
Channels	2
Current Feedback Topology	•
Phono EQ: Standard	•
HDAM version	SA3, SA2
EI Power Transformer	•
High Grade Audio Components	•
Balance / Bass / Treble / Loudness	• / • / • / •
OTHERS	
Linear Drive Power Supply	•
Source Direct	•
Standby Mode	•
INPUTS / OUTPUTS	
Audio Inputs	6
Phono Input: MM	•
Audio Outputs	2
Gold Plated Cinch	•
Speaker A / B	•
Speaker Terminals:	Transparent, Screw type
Number of terminals	4
D-Bus	•
Headphone Out	•

SPECIFICATIONS	
Power Output (8 / 4 Ohm RMS)	40 W / 55 W
Frequency Response	10 Hz - 50 kHz
Total Harmonic Distortion	0.01 %
Damping Factor	100
Input Sensitivity: MM	2.2 mV / 47 kOhm
Signal to Noise Ratio: MM	83 dB
Input Sensitivity: High level	200 mV / 20 kOhm
Signal to Noise Ratio: High level	103dB (2V input)
GENERAL	
Metal Front Panel	•
Power Consumption	350W
Standby Consumption	0.3 W
Auto Power off	•
Detachable Power Cable	•
Remote Control	RC002PMCD
System Remote Function	•
Maximum Dimensions (W x D x H)	17.32 x 14.57 x 4.13 in.
Weight	14.77 lbs.

Design and specifications are subject to change by Marantz without notice.

Perfect partner  
**CD5005**



CD Player